

PowerWalker MBS

Maintenance Bypass Switch

Provides maintenance bypass function

4x Schuko outlets (Master/Slave)

RJ11/RJ45 Surge Protection

Wall-mounting or desktop use flexibility

Supports all UPS up to 3000 VA



Item-No. 10120500

Product Features


PowerWalker MBS is used as an external power distribution unit in conjunction with UPS systems or large-scale voltage regulators. It allows to manually transferring the connected equipment to utility power via a bypass switch, permitting scheduled maintenance or UPS replacement without power interruption. Combined power distribution feature and the master/slave controlled design; it provides maintenance bypass function and power saving within a compact mechanism.

Supports all VFD, VI and VFI models up to 3000VA.

- Provides continuous power to connected equipment during UPS maintenance
- RJ11/RJ45 Surge Protection
- Master/Slave outlets design for energy saving
- Easy operation with simple rotary switch
- Plug-and-play connectivity for both input and output
- Suitable for all UPS up to 3000 VA



Master/Slave Schuko outlets



Bypass Switch



Energy saving

Technical Details

Product Features

Current Rating	10A
Voltage Rating	208/220/230/240VAC
Energy Saving Function	Yes (If power consumption in Master outlet is lower than 20W (±5W), it will shut off the power for slave outlets)

LED Indicators

Power LED	Green lighting
Master/Slave Function LED	Yellow lighting

Connections

Input from UPS	IEC C20
Output to UPS	Schuko
Master Output	1 x Schuko
Slave Output	3 x Schuko
Surge Protection	RJ11/RJ45 (in/out)

Product Details

Dimensions	166mm x 161mm x 89,2mm (D x W x H)
Colour	Black
Weight	1.0kg
Model Code	MBS

Environment

Temperature	0°C – 45°C
Humidity	20% - 90% RH (non- condensing)

Package Content

Package Content	PowerWalker MBS, manual
------------------------	-------------------------

Logistic Data

Giftbox Language	EN
Manual Language	EN
Dimension/Giftbox	191 x 119 x 231 mm
Weight/Giftbox	1.2kg
Dimension/carton	587 x 381 x 254 mm
Weight/carton	11.5kg
Pieces/carton	9
Pieces/palette	288
Item Number	10120500
EAN-Code	4260074973082
Warranty	24 Months (except battery)

Available accessories



Schuko Input -> IEC C19
Item Nr.: 91010018



Schuko Input -> IEC C13
Item Nr.: 91010017

Swiss Input -> IEC C19



IEC C19 -> IEC C20
Item Nr.: 91010028



IEC C13 -> IEC C20
Item Nr.: 91010041



IEC C14 -> IEC C19
Item Nr.: 91010040



IEC C14 -> Schuko
Converter
Item Nr.: 91015003



IEC C13 -> IEC C14
Item Nr.: 91010013

Version: EN 29/09/2014

We reserve the right for technical changes and mistakes